



Your one-stop classic coin-op arcade shop

Midway Ms. Pac/Pac-man PCB Repair Cap Kit

This repair kit is designed for the PCB and Aux card on the Pac-man and Ms. Pac game boards.

Be sure to check that the following parts are included in the kit.

Quantity	Part
4	10uf 25v
1	2200uf 25v
1	330uf 16v
2	10,000uf 10v
2	470uf 16v
1	4.7uf 35v
11	Total Parts

Be sure to install all the parts on the game board though many of the original parts seem to be working fine. Age, humidity, and temperature will cause the value of the electrolytic capacitors to change. Installing all of the parts will assure many more years of trouble free service.

Each capacitor is polarized and can only be inserted in one direction. Watch the markings for polarity on each capacitor. Axial capacitors generally have a strip and arrows pointing to the lead that matches the polarity of the symbol in the strip. The strip is most often the negative (-) symbol, but can sometimes be marked with a Positive (+) symbol, so look closely before installing each capacitor.

Make sure the game is unplugged and install the following parts:

- | | | |
|---------------------------------------|--|---|
| <input type="checkbox"/> C2 470uf 16v | <input type="checkbox"/> C7 10,000uf 10v | <input type="checkbox"/> C29 2200uf 25v |
| <input type="checkbox"/> C3 470uf 16v | <input type="checkbox"/> C8 10,000uf 10v | <input type="checkbox"/> C48 4.7uf 35v |
| <input type="checkbox"/> C5 10uf 25v | <input type="checkbox"/> C10 10uf 25v | <input type="checkbox"/> C51 330uf 16v |

Aux PCB (Ms Pac ONLY):

- | | |
|--------------------------------------|--------------------------------------|
| <input type="checkbox"/> C1 10uf 16v | <input type="checkbox"/> C2 10uf 16v |
|--------------------------------------|--------------------------------------|

CAUTION: Be sure to check your work before turning on the power.

If you have any problems feel free to call us for help.

MikesArcade.com
P.O. Box 130, 60 W. Main Street, Circleville, UT 84723 (435) 577-2258
Visit us at mikesarcade.com